

**21SW115** 8Ω


# LF Drivers - 21.0 Inches





- 3400 W continuous program power capacity
- 116 mm (4.5 in) split winding copper voice coil
- 30 1000 Hz response
- 97 dB sensitivity
- 60 mm peak-to-peak excursion before damage
- Neodymium magnet allows a very high force factor and linear excursion
- Double silicone spider with optimized compliance
- Ventilated voice coil gap for reduced power compression
- Aluminium demodulating ring for very low distortion



LF Drivers- 21.0 Inches







### **SPECIFICATIONS**

Nominal Diameter	530 mm (21.0 in)
Nominal Impedance	8 Ω
Minimum Impedance	6.2 Ω
Nominal Power Handling <sup>1</sup>	1700 W
Continuous power handling <sup>2</sup>	3400 W
Sensitivity (1W/1m) <sup>3</sup>	97.0 dB
Frequency Range	30 - 1000 Hz
Voice Coil Diameter	116 mm (4.5 in)
Winding Material	Copper
Former Material	Glass Fibre
Winding Depth	34.0 mm (1.34 in)
Magnetic Gap Depth	14.0 mm (0.55 in)
Flux Density	1.15 T

## DESIGN

Surround Shape	Triple Rol
Cone Shape	Radia
Magnet Material	Neodymium Inside Slug
Spider	Double Silicone
Pole Design	T-Pole
Woofer Cone Treatmen TW	t P Waterproof Both Sides
Recommended Enclosu	re 250.0 dm <sup>3</sup> (8.83 ft <sup>3</sup> )
Recommended Tuning	32 Hz

## PARAMETERS<sup>4</sup>

Resonance Frequency	30 Hz
Re	5.4 Ω
Qes	0.39
Qms	10.9
Qts	0.37
Vas	318.0 dm <sup>3</sup> (11.23 ft <sup>3</sup> )
Sd	1680.0 cm <sup>2</sup> (260.4 in <sup>2</sup> )
ηο	2.2 %
Xmax	± 14.0 mm
Xvar	± 16.0 mm
Mms	342.0 g
BI	30.1 Txm
Le	2.1 mH
EBP	76 Hz

### MOUNTING AND SHIPPING INFO

### SERVICE KIT

Overall Diameter	547 mm (21.5 in)	Recone kit
Bolt Circle Diameter	527 mm (20.7 in)	
Baffle Cutout Diameter	503.0 mm (19.8 in)	
Depth	249 mm (9.8 in)	
Flange and Gasket Thicknes	s 14 mm (0.53 in)	
Air Volume Occupied by Driv	er 15.0 dm <sup>3</sup> (0.53 ft <sup>3</sup> )	
Net Weight	14.0 kg (30.8 lb)	
Shipping Units	1	
Shipping Weight	16.3 kg (35.94 lb)	
Shipping Box 570x570x320 mm (22.	44x22.44x12.60 in)	

- 2 hours test made with continuous pink noise signal within the range Fs-10Fs. Power calculated on rated minumum impedance. Loudspeaker in free air.
  Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
  Applied RMS Voltage is set to 2.83 V for 8 ohms Nominal Impedance.
  Thiele-Small parameters are measured after a high level 20 Hz sine wave preconditioning test.