


8MBX51 8Ω

LF Drivers - 8.0 Inches









- 400 W continuous program power capacity
- 51 mm (2 in) aluminium voice coil
- 60 4000 Hz response
- 96.5 dB sensitivity
- Neodymium ring magnet assembly
- Aluminium ring allows a very low distortion figure
- Ventilated voice coil gap for reduced power compression




The MBX series mid-bass woofers from B&C Speakers offer acoustic designers a new range of high efficiency, wide bandwidth alternatives that are not currently available in the B&C range. These full-featured transducers incorporate lightweight neodymium motors, inside/outside wound copper clad aluminum wire voice coils, weatherproof impregnated paper cones, and a symmetrical inductance profile. The MBX Series is especially well suited for two-way loudspeaker enclosures.

LF Drivers- 8.0 Inches







SPECIFICATIONS

200 mm (8.0 in)
8 Ω
5.9 Ω
200 W
400 W
96.5 dB
60 - 4000 Hz
51 mm (2.0 in)
Aluminium
Glass Fibre
15.0 mm (0.59 in)
7.0 mm (0.28 in)
1.3 T

DESIGN

Surround Shape	Triple Rol
Cone Shape	Curvilinear
Magnet Material	Neodymium Ring
Spider	Single
Pole Design	T-Pole
Woofer Cone Treatment Waterproo	f Impregnated Cone
Recommended Enclosure	19.0 dm ³ (0.67 ft ³)
Recommended Tuning	63 Hz

PARAMETERS⁴

Resonance Frequency	60 Hz
Re	4.9 Ω
Qes	0.31
Qms	5.6
Qts	0.29
Vas	23.0 dm ³ (0.81 ft ³)
Sd	220.0 cm ² (34.1 in ²)
ηο	1.7 %
Xmax	± 6.0 mm
Xvar	± 8.0 mm
Mms	20.0 g
Bl	11.4 Txm
Le	0.4 mH
EBP	193 Hz

MOUNTING AND SHIPPING INFO

SERVICE KIT

Overall Diameter	225 mm (8.86 in)
Bolt Circle Diameter	210 mm (8.27 in)
Baffle Cutout Diameter	187.0 mm (7.36 in)
Depth	93 mm (3.66 in)
Flange and Gasket Thickne	ess 9 mm (0.35 in)
Air Volume Occupied by Dr	
	1.1 dm ³ (0.04 ft ³)
Net Weight	1.8 kg (3.97 lb)
Shipping Units	1
Shipping Weight	2.25 kg (4.96 lb)
Shipping Box 255x255x150 mm (

- 2 hours test made with continuous pink noise signal within the range Fs-10Fs. Power calculated on rated minumum impedance. Loudspeaker in free air.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Applied RMS Voltage is set to 2.83 V for 8 ohms Nominal Impedance.
 Thiele-Small parameters are measured after a high level 20 Hz sine wave preconditioning test.